



# LED T8 Ballast Compatibility Chart

Ballast Brand*	Part Number	Start Method	Lamp Connection	120Vac	277Vac	120Vac	277Vac	Ballast Factor	
				# of Lamps	# of Lamps	# of Lamps	# of Lamps	Type	Value
Ballast Wise	DXE118M8	PS	n.a					N	0.92
DAMAR	EL232-120/277HF(1688B)	IS	Parallel					N	
DAMAR	EL232DIM/120/277HF	DPS	Series						
DAMAR	EL232HL-120/277HF(1688D)	IS	Parallel					H	
DAMAR	EL332-120/277HF(3654C)	IS	Parallel					N	
DAMAR	EL332HL-120/277HF(3654H)	IS	Parallel					H	
DAMAR	EL432-120/277HF(3093B)	IS	Parallel					N	
DAMAR	EL432HL-120/277HF(3093C)	IS	Parallel					H	
EIKO	PM-2X32T8-UNV-IS	IS	Parallel	1	1	2	2	N	0.87
EIKO	PM-2X32T8-UNV-IS-L	IS	Parallel	1	1	2	2	L	0.77
EIKO	PM-3X32T8-UNV-IS	IS	Parallel	2	2	3	3	N	0.87
EIKO	PM-3X32T8-UNV-IS-H	IS	Parallel	2	2	3	3	H	1.18
EIKO	PM-3X32T8-UNV-IS-L	IS	Parallel	2	2	3	3	L	0.78
EIKO	PM-3X32T8-UNV-PS	PS	Series					N	0.88
EIKO	PM-3X32T8-UNV-PS-H	PS	Series					H	1.18
EIKO	PM-4X32T8-UNV-IS	IS	Parallel	3	3	4	4	N	0.88
EIKO	PM-4X32T8-UNV-IS-L	IS	Parallel	3	3	4	4	L	0.78
ESPEN	VE232MVHIPE	IS	Parallel	1	1	2	2	N	0.89
ESPEN	VE232MVHIPHE	IS	Parallel	1	1	2	2	H	1.19
ESPEN	VE232MVHIPL	IS	Parallel	1	1	2	2	L	0.77
ESPEN	VE232MVHRPHT3-AB	PS	Series					H	1.20
General Electric	GE132MAX-G-N	IS	n.a			1	1	H	0.88
General Electric	GE132MAX-H/ULTRA	IS	n.a			1	1	H	1.18
General Electric	GE132MAX-L/ULTRA	IS	n.a			1	1	H	0.78
General Electric	GE132MAXP-N/ULTRA	IS	n.a			1	1	N	0.88
General Electric	GE132MVPSN-V03	DPS	n.a					N	0.88
General Electric	GE232-120-RES	IS	Parallel	1	1	2	2	N	0.83
General Electric	GE232MAX347-N	IS	Parallel					N	0.87
General Electric	GE-232-MAX-H/Ultra	IS	Parallel	1	1	2	2	H	1.15
General Electric	GE232MAX-L/ULTRA	IS	Parallel	1	1	2	2	L	0.78
General Electric	GE232MAX-N/ULTRA	IS	Parallel	1	1	2	2	N	0.88
General Electric	GE232MAXP90-V60	IS	Parallel					H	1.18
General Electric	GE-232-MV-N	IS	Parallel	1	1	2	2	N	0.88
General Electric	GE232MV-N-DIY	IS	Parallel	1	1	2	2	N	0.88
General Electric	GE232MVPS-L-S30	DPS	Parallel					N	0.96
General Electric	GE232-MVPS-N	PS	Parallel	1	1	2	2	N	0.88
General Electric	GE-232-MV-PS-N	PS	Parallel	1	1	2	2	N	0.88
General Electric	GE332MAX-G-N	IS	Parallel	2	2	3	3	N	0.87
General Electric	GE332MAX-L/ULTRA	IS	Parallel	2	2	3	3	L	0.78
General Electric	GE332MAX-N/ULTRA	IS	Parallel	2	2	3	3	N	0.88
General Electric	GE332MAXP90-V60	IS	Parallel					H	1.18
General Electric	GE332MAXP-H/ULTRA	IS	Parallel	2	2	3	3	H	1.18
General Electric	GE332MV-N	IS	Parallel	2	2	3	3	N	0.87
General Electric	GE-332-MVPS-N	PS	Parallel	2	2	3	3	N	0.88
General Electric	GE332MVPSN-V03	DPS	Parallel					N	0.98
General Electric	GE432-120-RES	IS	Parallel	3		4		N	0.83



# LED T8 Ballast Compatibility Chart

Ballast Brand*	Part Number	Start Method	Lamp Connection	120Vac	277Vac	120Vac	277Vac	Ballast Factor	
				# of Lamps	# of Lamps	# of Lamps	# of Lamps	Type	Value
General Electric	GE432MAX347-N	IS	Parallel					N	0.88
General Electric	GE432MAX-G-N	IS	Parallel	3	3	4	4	N	0.88
General Electric	GE432MAX-H/ULTRA	IS	Parallel	3	3	4	4	H	1.18
General Electric	GE432MAX-H/ULTRA	IS	Parallel					H	1.18
General Electric	GE432MAX-L/ULTRA	IS	Parallel	3	3	4	4	L	0.78
General Electric	GE432MAX-N/ULTRA	IS	Parallel	3	3	4	4	N	0.88
General Electric	GE432MAXP90-S60	IS	Parallel					H	1.18
General Electric	GE432MV-N-42T	IS	Parallel	3	3	4	4	N	?
General Electric	GE432-MVPS-N	PS	Parallel	3	3	4	4	N	0.88
General Electric	GE432MVPS-N-V03	PS	Parallel					N	0.90
Halco	E432IS/120/R/SL	IS	Parallel	3		4		N	0.87
Halco	EP232IS/H/MV/HE	IS	Parallel					H	1.18
Halco	EP232IS/L/MV/HE	IS	Parallel					L	0.78
Halco	EP232IS/L/MV/SL	IS	Parallel	1	1	2	2	L	0.78
Halco	EP232IS/MV/HE	IS	Parallel	1	1	2	2	N	0.88
Halco	EP332IS/L/MV/HE	IS	Parallel					L	0.78
Halco	EP332IS/MV/HE	IS	Parallel	2	2	3	3	N	0.87
Halco	EP432IS/120/MC	IS	Parallel					N	0.88
Halco	EP432IS/L/MV/HE	IS	Parallel	3	3	4	4	L	0.78
Halco	EP432IS/MV/HE	IS	Parallel	3	3	4	4	N	0.88
HATCH	HL232BIS/UV/HE/W	IS	Parallel						
HATCH	HL432BIS/UV/HE/W	IS	Parallel						
HOWARD INDUSTRIES	E2/32IS-120MC	IS	Parallel	1		2		N	0.85
HOWARD INDUSTRIES	EP2/32IS/MV/MC/HE	IS	Parallel	1	1	2	2	N	0.89
HOWARD INDUSTRIES	EP2/32PRS/MV/MC/HE	PRS	Parallel					N	0.86
HOWARD INDUSTRIES	EP3/32IS/MV/MC/HE	IS	Parallel	2	2	3	3	N	0.88
HOWARD INDUSTRIES	EP3/32IS/MV/SC/HE	IS	Parallel	2	2	3	3	N	0.87
HOWARD INDUSTRIES	EP4/32IS/MV/MC/HE	IS	Parallel	3	3	4	4	N	0.88
HOWARD INDUSTRIES	EPH2/321S/MV/MC/HE	IS	Parallel	1	1	2	2	H	1.18
HOWARD INDUSTRIES	EPH4/32IS/MV/SC/HE	IS	Parallel	3	3	4	4	H	1.16
HOWARD INDUSTRIES	EPL2/32IS/MV/MC/HE	IS	Parallel	1	1	2	2	L	0.78
HOWARD INDUSTRIES	EPL3/32IS/MV/SC/HE	IS	Parallel	2	2	3	3	L	0.78
HOWARD INDUSTRIES	EPL4/32IS/MV/MC/HE	IS	Parallel	3	3	4	4	L	0.77
KEYSTONE	KTEB-132-1-TP-FC	RS	n.a					N	
KEYSTONE	KTEB-232LBF-1-TP-PIC-EV	IS	Parallel						
KEYSTONE	KTEB-232-UV-IS-N-P	IS	Parallel	1	1	2	2	N	0.87
KEYSTONE	KTEB-2C72-1-TP	PS	Parallel					N	0.97
KEYSTONE	KTEB-332-UV-IS-N-P	IS	Parallel	2	2	3	3	N	0.87
KEYSTONE	KTEB-432RIS-1-TP-SL	IS	Parallel	3		4		N	0.80
KEYSTONE	KTEB-432-UV-IS-N-P	IS	Parallel	3	3	4	4	N	0.87
LumaPro	4KGH1 EB-432IS-120	IS	Parallel	3		4		N	0.87
MAXLITE	MLEU322HEL/SC	IS	Parallel	1	1	2	2	L	0.83
MAXLITE	MLEU323H/SC	IS	Parallel	2	2	3	3	H	1.18
MAXLITE	MLEU324HE/SC	IS	Parallel	3	3	4	4	N	0.88
MAXLITE	SKEU322HEL/SC	IS	Parallel	1	1	2	2	L	0.77
MAXLITE	SKEU323L/SC	IS	Parallel	2	2	3	3	N	0.78



# LED T8 Ballast Compatibility Chart

Ballast Brand*	Part Number	Start Method	Lamp Connection	120Vac	277Vac	120Vac	277Vac	Ballast Factor	
				# of Lamps	# of Lamps	# of Lamps	# of Lamps	Type	Value
MAXLITE	SKEU324HE/SC	IS	Parallel	3	3	4	4	N	0.88
OSRAM SYLVANIA	QHE 1X32T8/UNV ISL-SC	IS	n.a			1	1	L	0.78
OSRAM SYLVANIA	QHE 1X32T8/UNV ISN-SC	IS	n.a			1	1	N	0.88
OSRAM SYLVANIA	QHE 2X32T8/UNV DIM-TC	PRS	Series					N	0.88
OSRAM SYLVANIA	QHE 2X32T8/UNV ISH-SC	IS	Parallel	1		2	2	H	1.20
OSRAM SYLVANIA	QHE 2X32T8/UNV ISL-SC	IS	Parallel	1	1	2	2	L	0.78
OSRAM SYLVANIA	QHE 2X32T8/UNV ISN-SC	IS	Parallel	1	1	2	2	N	0.88
OSRAM SYLVANIA	QHE 2X32T8/UNV PSH-HT	PRS	Parallel	1	1	2	2	H	1.18
OSRAM SYLVANIA	QHE 2X32T8/UNV PSN-MC	PRS	Parallel	1	1	2	2	N	0.88
OSRAM SYLVANIA	QHE 3X32T8/UNV ISH-SC	IS	Parallel	2	2	3	3	H	1.18
OSRAM SYLVANIA	QHE 3X32T8/UNV ISL-SC	IS	Parallel	2	2	3	3	L	0.78
OSRAM SYLVANIA	QHE 3X32T8/UNV ISN-SC	IS	Parallel	2	2	3	3	N	0.88
OSRAM SYLVANIA	QHE 3X32T8/UNV PSN-SC	PRS	Parallel	2	2	3	3	N	0.88
OSRAM SYLVANIA	QHE 4X32T8/UNV ISL-SC	IS	Parallel	3	3	4	4	L	0.78
OSRAM SYLVANIA	QHE 4X32T8/UNV ISN-SC	IS	Parallel	3	3	4	4	N	0.88
OSRAM SYLVANIA	QHE 4X32T8/UNV PSN-SC	PRS	Parallel	3	3	4	4	N	0.88
OSRAM SYLVANIA	QHE 4X32T8/UNV PSX-SC	PRS	Parallel	3	3	4	4	L	0.71
OSRAM SYLVANIA	QTP 1X32T8/UNV ISN-SC	IS	n.a			1	1	N	0.88
OSRAM SYLVANIA	QTP 2X32T8/UNV ISN-SC	IS	Parallel	1	1	2	2	N	0.88
OSRAM SYLVANIA	QTP 3X32T8/UNV ISN-SC	IS	Parallel	2	2	3	3	N	0.88
OSRAM SYLVANIA	QTP 3X32T8/UNV PSX-SC	PRS	Series					L	0.71
OSRAM SYLVANIA	QTP 4x32T8/UNV ISN-SC	IS	Parallel	3	3	4	4	N	0.88
OSRAM SYLVANIA	QTP2x32T8/UNV DIM-TC	DPS	Series					N	0.88
OSRAM SYLVANIA	QTP2x32T8/277 ISN-D	IS	Parallel						
OSRAM SYLVANIA	QTP3X32T8/UNV PSN-SC	PRS	Series					N	0.88
PES	PES120DET8	PS	Parallel					N	0.95
PES	PES120DET8-12SMT	PS	Parallel					N	0.95
PES	PES120ET8-12SMT-4	IS	?					N	0.88
Philips-Advance	ICN-1P32-N	IS	n.a			1	1	H	0.91
Philips-Advance	ICN-2P32-N	IS	Parallel	1	1	2	2	N	0.89
Philips-Advance	ICN-3P32-N	IS	Parallel	2	2	3	3	N	0.88
Philips-Advance	ICN-4P32-N	IS	Parallel	3	3	4	4	N	0.90
Philips-Advance	ICN-4P32-SC	IS	Parallel	3	3	4	4	N	0.89
Philips-Advance	IOP-1P32-N	IS	n.a			1	1	N	0.89
Philips-Advance	IOP-2P32HL-SC	IS	Parallel					H	1.18
Philips-Advance	IOP-2P32-LW-N	IS	Parallel	1	1	2	2	L	0.77
Philips-Advance	IOP-2P32-N	IS	Parallel	1	1	2	2	N	0.89
Philips-Advance	IOP-2PSP32-LW-N	PS	Parallel	1	1	2	2	L	0.71
Philips-Advance	IOP-2PSP32-N	PS	Parallel		1		2	N	0.94
Philips-Advance	IOP-2S32-SC	PS	Series					N	0.87
Philips-Advance	IOP-3P32-N	IS	Parallel					N	0.87
Philips-Advance	IOP-3PSP32-LW-SC	PS	Parallel	2	2	3	3	L	0.69
Philips-Advance	IOP-3PSP32-SC	PS	Parallel	2	2	3	3	N	0.88
Philips-Advance	IOP-4P32-HL-SC	IS	Parallel			4		H	1.18
Philips-Advance	IOP-4P32-LW-N	IS	Parallel	3	3	4	4	L	0.77
Philips-Advance	IOP-4P32-N	IS	Parallel	3	3	4	4	N	0.87



# LED T8 Ballast Compatibility Chart

Ballast Brand*	Part Number	Start Method	Lamp Connection	120Vac	277Vac	120Vac	277Vac	Ballast Factor	
				# of Lamps	# of Lamps	# of Lamps	# of Lamps	Type	Value
Philips-Advance	IOP-4PSP32-LW-SC	PS	Parallel	3	3	4	4	L	0.69
Philips-Advance	IOP-4PSP32-SC	PS	Parallel	3	3	4	4	N	0.89
Philips-Advance	IOPA-1P32-N	IS	n.a			1	1	H	0.88
Philips-Advance	IOPA-2P32HL-SC	IS	Parallel	1	1	2	2	H	1.18
Philips-Advance	IOPA-2P32-N	IS	Parallel	1	1	2	2	N	0.89
Philips-Advance	IOPA-3P32-LW-N	IS	Parallel	2	2	3	3	L	0.76
Philips-Advance	IOPA-3P32-N	IS	Parallel					N	0.86
Philips-Advance	IOPA-4P32-HL-SC	IS	Parallel	3	3	4	4	H	1.18
Philips-Advance	IOPA-4P32-N	IS	Parallel					N	0.87
Philips-Advance	IZT-2PSP32-SC	DPS	Parallel					N	1.00
Philips-Advance	IZT-2S32-SC	DPS	Series					N	1.00
Philips-Advance	REB-2P32-SC	IS	Parallel					N	0.88
Philips-Advance	REB-4P32-SC	IS	Parallel	3		4		N	0.81
Philips-Advance	REZ-3S32-SC	DPS	Series					N	0.97
Philips-Advance	VEL-2P32-SC	IS	Parallel						
PLUSRITE	BAF232IS/MV	IS	Parallel	1	1	2	2	N	0.89
PLUSRITE	BAF332IS/MV	IS	?	2	2	3	3	?	?
Robertson	ISU232T8120 3P20116	IS	Parallel	1		2		N	0.88
Robertson	RSZ132T8120	PS	n.a					N	0.80
SOLA	E-758-F-232-SC	IS	Parallel	1	1	2	2	N	0.88
SOLA	E-758-U-232-MC	IS	Parallel	1	1	2	2	N	0.88
SUNPARK	120-1/32IS HPF	IS	n.a			1		N	0.88
SUNPARK	120-3/32IS MP,F	IS	Parallel	2		3		N	0.88
SUNPARK	LC 12011T	PS	n.a					?	?
SUNPARK	LC 12013T	PS	n.a			1		?	?
SUNPARK	SL15T	RS	Parallel			2		N	0.88
SUNPARK	U-1/32PSE	PS	n.a					N	0.88
SUNPARK	U-2/32IS HBF	IS	Parallel	1	1	2	2	H	1.18
SUNPARK	U-2/32ISE-LBF	IS	Parallel	1	1	2	2	L	0.78
SUNPARK	U-2/32PSE	RS	Series					N	0.88
SUNPARK	U-2/32PSE-HBF	RS	Series					H	1.15
SUNPARK	U-232PS3	RS	Series					N	0.88
SUNPARK	U-232PS3-HBF	RS	Series					H	1.15
SUNPARK	U-3/32ISE	IS	Parallel	2	2	3	3	N	0.88
SUNPARK	U-3/32ISE-HBF	IS	Parallel	2	2	3	3	H	1.18
SUNPARK	U-4/32IS HBF	IS	Parallel	3	3	4	4	H	1.18
SUNPARK	U-4/32IS HP,F	IS	Parallel	3	3	4	4	N	0.88
SUNPARK	U-4/32ISE-LBF	IS	Parallel	3	3	4	4	L	0.88
Superior Life	70201	IS	Parallel	1		2	2	N	0.88
Superior Life	70210	PS	Parallel	1	1	2	2	N	0.88
Superior Life	70211	PS	Parallel	3	3	4	4	N	0.87
TCP	E2P32ISUNVHE	IS	Parallel	1	1	2	2	H	1.18
TCP	E3P32ISUNVE	IS	Parallel	2	2	3	3	N	0.88
TCP	E3P32ISUNVLE	IS	Parallel	2	2	3	3	L	0.78
TCP	E4P32ISUNVE	IS	Parallel	3	3	4	4	N	0.88
TCP	E4P32ISUNVHE	IS	Parallel	3	3	4	4	H	1.18



## LED T8 Ballast Compatibility Chart

Ballast Brand*	Part Number	Start Method	Lamp Connection	120Vac		277Vac		Ballast Factor	
				# of Lamps	# of Lamps	# of Lamps	# of Lamps	Type	Value
TCP	E4P32ISUNVLE	IS	Parallel	3		4	4	L	0.78
Universal Lighting Technologies	B132IUNVHP-N	IS	n.a			1	1	N	0.88
Universal Lighting Technologies	B232I120RES-A	IS	Parallel	1		2		N	0.88
Universal Lighting Technologies	B232IUNVEL-A	IS	Parallel	1	1	2	2	L	0.77
Universal Lighting Technologies	B232IUNVHEH-A	IS	Parallel	1	1	2	2	H	1.18
Universal Lighting Technologies	B232IUNVHP-B	IS	Parallel						
Universal Lighting Technologies	B232IUNVHP-N	IS	Parallel	1	1	2	2	N	0.88
Universal Lighting Technologies	B232PU104S50A	PRS	Parallel						
Universal Lighting Technologies	B232PUNVHE-B	PS	Parallel	1	1	2	2	N	0.88
Universal Lighting Technologies	B233IUNVHE-A	IS	Parallel	1	1	2	2	N	0.87
Universal Lighting Technologies	B332IUNVHP-A	IS	Parallel	2	2	3	3	N	0.88
Universal Lighting Technologies	B332PUNVHE-A	PS	Parallel	2	2	3	3	N	0.88
Universal Lighting Technologies	B332PUNVHEH-A	PS	Parallel						
Universal Lighting Technologies	B432I120RES-A	IS	Parallel	3		4		N	0.80
Universal Lighting Technologies	B432IUNVHE L-A	IS	Parallel	3	3	4	4	L	0.77
Universal Lighting Technologies	B432IUNVHP-A	IS	Parallel	3	3	4	4	N	0.88
Universal Lighting Technologies	B432PUNVHE-A	PS	Parallel	3	3	4	4	N	0.87
Watran	DBG32N-MV-TP-PS-HL	PS	Series					?	?
WORK HORSE	WHCG4-120-T8-IS	IS	Parallel	3		4		N	0.86
WORK HORSE	WHSG3-UNV-T8-IS	IS	Parallel	2	2	3	3	N	0.99
WORK HORSE	WHSG4-UNV-T8-IS	IS	Parallel	3	3	4	4	N	0.96

Applies to the following Satco products:	<b>S9246, S9247, S9248, S9249</b>	<b>9 Watt 2 ft. T8</b>	<b>Ballast Factors:</b> L - Low N - Normal H - High
	<b>S9290, S9291, S9292, S9293</b>	<b>11 Watt 3 ft. T8</b>	
	<b>S9234, S9235, S9236, S9237</b>	<b>14 Watt 4 ft. T8</b>	
	<b>S9275, S9276, S9277, S9278</b>	<b>17 Watt 4 ft. T8</b>	

This list is current as of Mar. 2016. We are continuously testing for compatible ballasts. Please check back for updates.

\* All trademarks are the property of their respective owners

Copyright© 2016	Distribution Centers:	National Toll-Free:	110 Heartland Blvd.
Satco Products, Inc.	New York, Florida,	800-43-SATCO	Brentwood, NY 11717
All Rights Reserved.	Texas, Washington,	(800-437-2826)	PH 631-243-2022
Rev: March 8, 2016-b	California, Puerto Rico	<b>www.satco.com</b>	FX 631-243-2027