



LED 4-Pin PL Electronic Dimmer Compatibility Chart

Brand*	Ballast		Dimmer		Dimming Type	# Of Lamps	1 Lamp		2 Lamps	
	Model No.	Brand*	Model No.	Brand*			120V	277V	120V	277V
Osram	QTP 2X26CF/UNV DIM DM	LEDdynamics	LUXdrive A019		0-10V	2	F	F	F	F
Philips-Advance	REB-2S26-M1-LS-DIM	Lutron	DIVA DVELV-300P		Triac	2	F	NA	F	NA
Philips-Advance	REB-2S26-M1-LS-DIM	Lutron	SKYLARK CTCL-153P		Triac	2	NC	NA	NC	NA
Philips-Advance	REB-2S26-M1-LS-DIM	Lutron	SKYLARK CT-603PG		Triac	2	L,H	NA	H	NA
Philips-Advance	REB-2S26-M1-LS-DIM	Lutron	SKYLARK S-600P		Triac	2	NC	NA	NC	NA
Philips-Advance	REB-2S26-M1-LS-DIM	Lutron	Ariadni AY-600P		Triac	2	L,H	NA	F	NA
Philips-Advance	REB-2S26-M1-LS-DIM	Leviton	DECORA 6633P		Triac	2	F	NA	F	NA
Philips-Advance	REB-2S26-M1-LS-DIM	Leviton	DECORA IPI06		Triac	2	NC	NA	NC	NA
Philips-Advance	REB-2S26-M1-LS-DIM	Lutron	DIVA DVCL-153P		Triac	2	F	NA	F	NA
Philips-Advance	REB-2S26-M1-LS-DIM	Lutron	NOVQT NTELV-300		Triac	2	F	NA	L	NA
Philips-Advance	REB-2S26-M1-LS-DIM	Lutron	DIVA DVLV-603P		Triac	2	L	NA	L	NA
Philips-Advance	REB-2S26-M1-LS-DIM	Lutron	SKYLARK CT-103P		Triac	2	L	NA	L	NA
Philips-Advance	REZ-2T42-M3-BS	Lutron	DIVA DVELV-300P		Triac	2	NC	NA	NC	NA
Philips-Advance	REZ-2T42-M3-BS	Lutron	SKYLARK CTCL-153P		Triac	2	L	NA	L	NA
Philips-Advance	REZ-2T42-M3-BS	Lutron	SKYLARK CT-603PG		Triac	2	NC	NA	NC	NA
Philips-Advance	REZ-2T42-M3-BS	Lutron	SKYLARK S-600P		Triac	2	F	NA	F	NA
Philips-Advance	REZ-2T42-M3-BS	Lutron	Ariadni AY-600P		Triac	2	F	NA	F	NA
Philips-Advance	REZ-2T42-M3-BS	Leviton	DECORA 6633P		Triac	2	NC	NA	NC	NA
Philips-Advance	REZ-2T42-M3-BS	Leviton	DECORA IPI06		Triac	2	F	NA	F	NA
Philips-Advance	REZ-2T42-M3-BS	Lutron	DIVA DVCL-153P		Triac	2	F	NA	F	NA
Philips-Advance	REZ-2T42-M3-BS	Lutron	NOVQT NTELV-300		Triac	2	NC	NA	NC	NA
Philips-Advance	REZ-2T42-M3-BS	Lutron	DIVA DVLV-603P		Triac	2	F	NA	F	NA
Philips-Advance	REZ-2T42-M3-BS	Lutron	SKYLARK CT-103P		Triac	2	NC	NA	NC	NA
Philips-Advance	REZ-1T42-M2-BS	Lutron	DIVA DVELV-300P		Triac	1	L	NA	-	-
Philips-Advance	REZ-1T42-M2-BS	Lutron	SKYLARK CTCL-153P		Triac	1	L	NA	-	-
Philips-Advance	REZ-1T42-M2-BS	Lutron	SKYLARK CT-603PG		Triac	1	L	NA	-	-
Philips-Advance	REZ-1T42-M2-BS	Lutron	SKYLARK S-600P		Triac	1	NC	NA	-	-
Philips-Advance	REZ-1T42-M2-BS	Lutron	Ariadni AY-600P		Triac	1	F	NA	-	-
Philips-Advance	REZ-1T42-M2-BS	Leviton	DECORA 6633P		Triac	1	NC	NA	-	-
Philips-Advance	REZ-1T42-M2-BS	Leviton	DECORA IPI06		Triac	1	NC	NA	-	-
Philips-Advance	REZ-1T42-M2-BS	Lutron	DIVA DVCL-153P		Triac	1	NC	NA	-	-
Philips-Advance	REZ-1T42-M2-BS	Lutron	NOVQT NTELV-300		Triac	1	L	NA	-	-
Philips-Advance	REZ-1T42-M2-BS	Lutron	DIVA DVLV-603P		Triac	1	L	NA	-	-
Philips-Advance	REZ-1T42-M2-BS	Lutron	SKYLARK CT-103P		Triac	1	L	NA	-	-
Philips-Advance	REZ-1T42-M2-BS	Lutron	Ariadni AYCL-153P		Triac	1	L	NA	-	-
Philips-Advance	REZ-1T42-M2-BS	Leviton	DECORA 6842		Triac	1	F	NA	-	-
Philips-Advance	VEZ-1T42-M2-LD	Lutron	NOVQ NA-10-277		Triac	1	NA	L	-	-
Philips-Advance	VEZ-2Q26-M2-LD	Lutron	NOVQ NA-10-277		Triac	1	NA	L	-	-
Philips-Advance	VEZ-1T42-M2-BS	Lutron	NOVQ NA-10-277		Triac	1	NA	L	-	-
Philips-Advance	IZT-2S26-M5-LD	LEDdynamics	LUXdrive A019		0-10V	2	F	F	F	F

Applies to the following Satco products:

- S9850, S9851, S9852, S9853, S9858, S9859, S9860, S9861**
S29850, S29851, S29852, S29853, S29858, S29859,
S29860, S29861

- F** Flicker after >2s start-up (NC)
- N** Acoustic noise >20dB
- L** min LED current > 20% LED current without Dimmer
- H** max LED current < 80% LED current without Dimmer
- NC** Not compatible
- NA** Not applicable

This list is current as of Jan. 2021. We are continuously testing for compatible ballasts. Please check back for updates.

* All trademarks are the property of their respective owners

110 Heartland Blvd.
 Brentwood, NY 11717
 PH 631-243-2022
 FX 631-243-2027

Distribution Centers
 New York, Florida,
 Texas, Washington,
 California, Puerto Rico

National Toll-Free
 800-43-SATCO
 (800-437-2826)
www.satco.com

Copyright© 2017
 Satco Products, Inc.
 All Rights Reserved.
 Rev: December 27, 2017