



### LED T8 Ballast Compatibility Chart

Ballast Brand*	Part Number	# Of Lamps	Start Method	Lamp Connection	1 Lamp		2 Lamps		3 Lamps		4 Lamps		Ballast Type	Factor Value
					120V	277V	120V	277V	120V	277V	120V	277V		
ACT	ACT 2P32ISUNVE	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	N	0.89
Antron Electronics	A32T8MICLO	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	L	0.78
Arcata	ACT 3P32ISUNVLE	3	IS	Parallel	-	-	✓	✓	✓	✓	-	-	L	0.78
Cooper Lighting	CL-432ISUNV-R1-B	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	H	1.18
Damar	EL232-120/277HF(1688B)	2	IS	Parallel	✓	P	✓	✓	-	-	-	-	N	NA
Damar	EL232HL-120/277HF(1688D)	2	IS	Parallel	✓	P	✓	✓	-	-	-	-	H	NA
Damar	EL332-120/277HF(3654C)	3	IS	Parallel	-	-	✓	✓	✓	✓	-	-	N	NA
Damar	EL332HL-120/277HF(3654H)	3	IS	Parallel	-	-	✓	P	✓	P	-	-	H	NA
Damar	EL432-120/277HF(3093B)	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	N	NA
Damar	EL432HL-120/277HF(3093C)	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	H	NA
Eiko	PM-2X32T8-UNV-IS-L	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	L	0.77
Eiko	PM-3X32T8-UNV-IS	3	IS	Parallel	-	-	✓	✓	✓	✓	-	-	N	0.87
Eiko	PM-3X32T8-UNV-IS-H	3	IS	Parallel	-	-	✓	✓	✓	✓	-	-	H	1.18
Eiko	PM-3X32T8-UNV-IS-L	3	IS	Parallel	-	-	✓	✓	✓	✓	-	-	L	0.78
Eiko	PM-4X32T8-UNV-IS	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	N	0.88
Eiko	PM-4X32T8-UNV-IS-L	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	L	0.78
Eiko	PM-2X32T8-UNV-IS	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	N	0.87
Eiko	PM-2x32T8-UNV-IS-H	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	H	1.18
Espen	VE232MVHIPE	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	N	0.89
Espen	VE232MVHIPHE	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	H	1.19
Espen	VE232MVHIPLE	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	L	0.77
General Electric	GE-232-MV-N	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	N	0.88
General Electric	GE232MAX-N/ULTRA	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	N	0.88
General Electric	GE432MAX-H/ULTRA	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	H	1.18
General Electric	GE432MAX-L/ULTRA	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	L	0.78
General Electric	GE-232-MAX-H/Ultra	2	IS	Parallel	NC	NC	NC	NC	-	-	-	-	H	1.15
General Electric	GE432MAX-G-N	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	N	0.88
General Electric	GE132MAX-G-N	1	IS	NA	NC	NC	-	-	-	-	-	-	N	0.88
General Electric	GE132MAX-H/ULTRA	1	IS	NA	NC	NC	-	-	-	-	-	-	H	1.18
General Electric	GE132MAX-L/ULTRA	1	IS	NA	NC	NC	-	-	-	-	-	-	L	0.78
General Electric	GE132MAXP-N/ULTRA	1	IS	NA	✓	✓	-	-	-	-	-	-	N	0.88
General Electric	GE232MV-N-DIY	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	N	0.88
General Electric	GE232MAX-L/ULTRA	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	L	0.78
General Electric	GE232MAX347-N	2	IS	Parallel	NA	F	NA	F	-	-	-	-	H	1.02
General Electric	GE332MV-N	3	IS	Parallel	-	-	✓	P	✓	P	-	-	N	0.87
General Electric	GE332MAX-N/ULTRA	3	IS	Parallel	-	-	✓	P	✓	✓	-	-	N	0.88
General Electric	GE332MAX-L/ULTRA	3	IS	Parallel	-	-	✓	P	✓	P	-	-	L	0.78
General Electric	GE332MAX-G-N	3	IS	Parallel	-	-	✓	P	✓	✓	-	-	N	0.87
General Electric	GE432-120-RES	4	IS	Parallel	-	-	-	-	✓	NA	✓	NA	N	0.83
General Electric	GE432MV-N-42T	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	N	0.93
General Electric	GE432MAX-N/ULTRA	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	N	0.88
General Electric	GE432MAX347-N	4	IS	Parallel	-	-	-	-	NA	347V ✓	NA	347V ✓	N	0.94
General Electric	GE232MAXP90-V60	2	IS	Parallel	✓	P,T	✓	✓	-	-	-	-	H	1.18
General Electric	GE332MAXP90-V60	3	IS	Parallel	-	-	✓	✓	-	✓	-	-	H	1.18
General Electric	GE432MAXP90-S60	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	H	1.18
General Electric	GE432MAX-H/ULTRA	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	H	1.18
General Electric	GE432MAX90-S60	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	H	1.18
General Electric	GE332MAXP-L/ULTRA	3	IS	Parallel	-	-	✓	✓	✓	✓	-	-	L	0.77
General Electric	GE232MAX-G-N	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	N	0.88
General Electric	GE-232-MAX-H-42T	2	IS	Parallel	HT	HT	HT	HT	-	-	-	-	H	NA
General Electric	GE432MAX-H-42T	4	IS	Parallel	-	-	-	-	✓	✓	✓	T	H	NA
General Electric	332MAX-H-84TS	3	IS	Parallel	-	-	✓	✓	✓	T	-	-	H	NA
General Electric	332MAX-H-42T	3	IS	Parallel	-	-	✓	✓	✓	✓	-	-	H	NA
General Electric	GE432MAX-G-H	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	H	1.18
General Electric	GE232-MVPS-N	2	PS	Parallel	✓	✓	✓	✓	-	-	-	-	N	0.88
General Electric	GE-332-MVPS-N	3	PS	Parallel	-	-	✓	✓	✓	✓	-	-	N	0.88
General Electric	GE-232-MV-PS-N	2	PS	Parallel	✓	✓	✓	✓	-	-	-	-	N	0.88
General Electric	GE132MVPSPN-V03**	1	DPS	NA	✓	✓	-	-	-	-	-	-	N	0.88
Halco	EP232IS/MV/HE	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	N	0.88
Halco	EP332IS/MV/HE	3	IS	Parallel	-	-	✓	✓	✓	✓	-	-	N	0.87
Halco	EP432IS/MV/HE	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	N	0.88
Halco	EP432IS/L/MV/HE	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	L	0.78
Halco	EP232IS/L/MV/HE	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	L	0.78
Halco	EP232IS/H/MV/HE	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	H	1.18
Halco	EP332IS/L/MV/HE	3	IS	Parallel	-	-	✓	✓	✓	✓	-	-	L	0.78
Halco	EP432IS/120/MC	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	n	0.88
Hatch	HL232BIS/UV/HE/W	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	N	0.90
Hatch	HL432BIS/UV/HE/W	4	IS	Parallel	-	-	-	-	✓	P	✓	✓	N	0.90
Howard Industries	EPH4/32IS/MV/SC/HE	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	H	1.16
Howard Industries	EP3/32IS/MV/SC/HE	3	IS	Parallel	-	-	✓	✓	✓	✓	-	-	N	0.87
Howard Industries	EPL4/32IS/MV/MC/HE	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	L	0.77
Howard Industries	EPH2/32IS/MV/MC/HE	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	H	1.18
Howard Industries	E2/32IS-120MC	2	IS	Parallel	P,T	NA	PT	NA	-	-	-	-	N	0.85
Howard Industries	EPL2/32IS/MV/MC/HE	2	IS	Parallel	✓	P,T	✓	P	-	-	-	-	L	0.78
Howard Industries	EPL3/32IS/MV/SC/HE	3	IS	Parallel	-	-	✓	✓	✓	✓	-	-	L	0.78
Howard Industries	EP4/32IS/MV/MC/HE	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	N	0.88
Howard Industries	EP2/32IS/MV/MC/HE	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	N	0.89
Howard Industries	EP3/32IS/MV/MC/HE	3	IS	Parallel	-	-	✓	✓	✓	✓	-	-	N	0.88





### LED T8 Ballast Compatibility Chart

Ballast Brand*	Part Number	# Of Lamps	Start Method	Lamp Connection	1 Lamp		2 Lamps		3 Lamps		4 Lamps		Ballast Type	Factor Value
					120V	277V	120V	277V	120V	277V	120V	277V		
Sunpark	U-3/32ISE	3	IS	Parallel	-	-	✓	✓	✓	✓	-	-	N	0.88
Sunpark	U-3/32ISE-HBF	3	IS	Parallel	-	-	✓	✓	✓	✓	-	-	H	1.18
Sunpark	120-3/32IS MPF	3	IS	Parallel	-	-	✓	NA	✓	NA	-	-	N	0.88
Sunpark	U-4/32IS HP,F	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	N	0.88
Sunpark	U-4/32IS HBF	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	H	1.18
Sunpark	U-4/32ISE-LBF	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	L	0.77
Sunpark	SL15T	2	PS	Series	NC	NA	NC	NA	-	-	-	-	N	0.88
Superior Life	70201	2	IS	Parallel	F	F	✓	✓	-	-	-	-	N	0.88
Sylvania	QT 3x32/277 IS	3	IS	Parallel	-	-	✓	✓	✓	✓	-	-	NA	Parallel
TCP	E4P32ISUNVLE	4	IS	Parallel	-	-	-	-	F	F	F	F	L	0.78
TCP	E3P32ISUNVE	3	IS	Parallel	-	-	✓	✓	✓	✓	-	-	N	0.88
TCP	E3P32ISUNVLE	3	IS	Parallel	-	-	F	F	✓	✓	-	-	L	0.78
TCP	E4P32ISUNVE	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	N	0.88
TCP	E4P32ISUNVHE	54	IS	Parallel	-	-	-	-	-	-	-	-	N	1.18
TCP	TCP3P32ISUNVH	3	IS	Parallel	-	-	HT	HT	HT	HT	-	-	H	1.18
TCP	E3P32ISUNVHE	3	IS	Parallel	-	-	HT	HT	HT	HT	-	-	H	NA
Topaz	B232IUNVHEH/A-TPZ	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	H	1.18
Topaz	B432IUNVHEH/A-TPZ	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	H	1.18
Universal Lighting Technologies	B232IUNVHP-N	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	N	0.88
Universal Lighting Technologies	B232IUNVEL-A	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	L	0.77
Universal Lighting Technologies	B233IUNVHE-A	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	N	0.87
Universal Lighting Technologies	B432IUNVHE L-A	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	L	0.77
Universal Lighting Technologies	B232IUNVHEH-A	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	N	118.00
Universal Lighting Technologies	B332IUNVHP-A	3	IS	Parallel	-	-	✓	✓	✓	✓	-	-	N	0.88
Universal Lighting Technologies	B432IUNVHP-A	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	N	0.88
Universal Lighting Technologies	B232I120RES-A	2	IS	Parallel	✓	NA	✓	NA	-	-	-	-	N	0.88
Universal Lighting Technologies	B132IUNVHP-N	1	IS	NA	✓	✓	-	-	-	-	-	-	N	0.88
Universal Lighting Technologies	B232IUNVHP-B	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	N	0.88
Universal Lighting Technologies	B232IUNV-C	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	N	0.88
Universal Lighting Technologies	B432IUNVHE-A	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	N	0.87
Universal Lighting Technologies	B432IUNVHEH-E	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	H	1.15
Universal Lighting Technologies	B232I277RH-A	4	IS	Parallel	-	-	-	NA	P,T	NA	✓	✓	H	1.09
Universal Lighting Technologies	B332IHRVHB-E	3	IS	Parallel	-	-	NC	NC	NC	NC	-	-	H	NA
Universal Lighting Technologies	B432PUNVHE-A	4	PS	Parallel	-	-	-	-	✓	✓	✓	✓	N	0.87
Universal Lighting Technologies	B232PUNVHE-B	2	PS	Parallel	✓	PT	✓	PT	-	-	-	-	N	0.88
Watran	DB-232N-MV-TP-HE	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	N	0.87
Watran	DB-332N-MV-TP-HE	3	IS	Parallel	-	-	✓	✓	✓	✓	-	-	N	0.87
Watran	DB-432N-MV-TP-HE	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	N	0.87
Watran	DB-432L-MV-TP-HE	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	L	0.77
Watran	DB-232N-MV-TP-HE (SC)	2	IS	Parallel	✓	✓	✓	✓	-	-	-	-	N	0.87
Watran	DBG32N-MV-TP-PS-HL	3	PS	NA	-	-	NC	NC	NC	NC	-	-	H	NA
Work Horse	WHSG3-UNV-T8-IS	3	IS	Parallel	-	-	✓	✓	✓	✓	-	-	N	0.99
Work Horse	WHSG4-UNV-T8-IS	4	IS	Parallel	-	-	-	-	✓	✓	✓	✓	N	0.96

**F** Flicker after >2s start-up  
**N** Acoustic noise >20dB  
**P** PF <0.85  
**T** THD >25%  
**HT** High Temperature  
**NC** Not compatible  
**NA** Not applicable  
**\*\*** Dimmable Ballast

**Ballast Factors:**  
 L - Low  
 N - Normal  
 H - High

Applies to the following Satco products: **S29938, S29939, S29940, S29941**

This list is current as of Nov. 2018. We are continuously testing for compatible ballasts. Please check back for updates.

\* All trademarks are the property of their respective owners

110 Heartland Blvd.  
 Brentwood, NY 11717  
 PH 631-243-2022  
 FX 631-243-2027

Distribution Centers  
 New York, Florida,  
 Texas, Washington,  
 California, Puerto Rico

National Toll-Free  
 800-43-SATCO  
 (800-437-2826)  
 www.satco.com

Copyright© 2018  
 Satco Products, Inc.  
 All Rights Reserved.  
 Rev: November 7, 2018